


SP64AE Instructions



SP64AE SPI RGB CCT LED Controller



1.Brief:

SPI five-channel addressable RGB CCT LED controller, with unique dynamic, music and DIY effects to meet your lighting and ambiance needs.

2.Features:


1. Support App control and 2.4G remote control;
2. Support up to 300 single-wire RZ RGB CCT LED driver ICs;
3. Built-in a variety of music and dynamic effects, support effects pause, multi-parameter adjustable;
4. Capture music through the phone microphone, player streamer and on-board microphone;
5. Support effect collection;
6. support DIY effects;
7. With a variety of ON/OFF animation effects;
8. With sequential channel calibration and ON/OFF timer functions;
9. Support OTA firmware upgrade.

3.APP:



- 1.SP64AE supports App control for iOS and Android devices.
- 2.Apple devices require iOS 10.0 or higher, and Android devices require Android 4.4 or higher.
- 3.You can search “BanlanX” in App Store or Google Play to find the APP, or scan the QR code to download and install.


Operations

- Open the App, click the + icon in the top right corner of the home page to add device;
- Click the  icon in the upper right corner of the App to enter the settings page, where you can modify the device name, set the timings, set the on/off effect, OTA firmware upgrade, etc.

4. Work With 2.4G Remote Control:

The 2.4G remote control models (RA4) matched with SP64AE are as follows:

- Support one-to-many control, one remote control can control multiple controllers.
- Support many-to-one control, each controller can bind up to 5 remote controls.



5. Technical Parameters:

Working Voltage: DC5V~24V	Working Current: 12mA~25mA
Working Temp: -20°C~60°C	Dimension: 55mm*26mm*12mm (not including the wires)

6. Wiring

